

Stereo Amplifier

PM4001P



A high quality entry level stereo amplifier, with 19" rack-mounting kit and remote control, the PM40001P replaces the PM4400P in the Marantz Professional *Studioline* range. It's featureset includes full record out selector (allowing simultaneous record and listen of separate sources), tone defeat circuit and two pairs of switchable speaker outputs (for multi-room and multi-speaker applications).

Key Features

- Output power 2 x 30 Watts (8 ohms)
- Solid metal front and rigid chassis construction
- Full record out selector
- Tone control & loudness function
- Tone defeat circuit
- Two pairs of speaker outputs
- D-Bus & system IR remote control
- 3U

PM4001P

Specifications

General

Available colours	Black
Metal Front Panel	
Remote Control	RC4001PM
System Remote Function System	
Detachable Power Cable	
Maximum Dimensions(W x D x H):	440 x 343 x 161 mm
Weight	6.0 kg

Power Consumption

Power Consumption	100 Watts
Power Output	(8/4 Ohm RMS) 30/40 Watts

Audio

Frequency Range	10Hz-30kHz (25W, 0.06%)
Frequency Response	10Hz-50kHz (+0,-1dB)

Inputs/Outputs

Input Sensitivity	MM 2.5 mV / 47 kOhm
Input Sensitivity	High level150mV /20kOhm
Signal to Noise Ratio	High level105 dB
Signal to Noise Ratio	MM 80dB

Total Harmonic Distortion	0.005%
Damping factor	80

Design and specifications are subject to change by Marantz without notice.



Stereo Amplifier **PM4001P**

D&M Professional Europe
 Kingsbridge House, Padbury Oaks, 575-583 Bath Road, Longford, Middlesex, UB7 0EH, UK
 Tel: +44 (0)1753 680023 Fax: +44(0)1753 686020 www.d-mpro.eu.com/pm4001p